

RON FRANCIS
Wiring

DL-39
Dome Light
3 7/8 Diameter

The round style dome light features a polished double radius edge with a molded plastic lens. The unit is supplied with two 5/8 inch phillips screws for easy mounting.

Mounting

To remove lense, insert a business card or similar thickness object between lense and base. Move around until one of the three tabs is felt. Push in the lense toward the center to release the lense.

Use the base as a templet for pre-drilling the mounting holes.

Caution!

Do not crush the wires between the light base and mounting surface. Drill two holes in the mounting surface if necessary to accommodate the wires. Use grommets to protect the wires running through any metal surface. Test this circuit for proper operation prior to reinstalling the head liner.

Wiring: Run a fused 12 volt battery feed (hot all the time) to the red wire running from the light. Run a wire from each door jam switch (if used) and the dome light control terminal on the head light switch connecting all wires to the gray wire running from the light as shown in the diagram below. If your door jam switches have two terminals, ground the other terminal on the switch to a good ground.

