



7801 MULTI FIRE IGNITION CONTROLLER INSTALLATION

WIRING

LARGE RED WIRE

POSITIVE BATTERY TERMINAL

LARGE BLACK WIRE

VEHICLE GROUND

SMALL RED WIRE

SWITCHED 12V

ORANGE WIRE

POSITIVE COIL TERMINAL

BLACK WIRE

NEGATIVE COIL TERMINAL

TRIGGER WIRES - ONLY USE THE WHITE WIRE OR THE
VIOLET GREEN WIRES NEVER USE BOTH TO TRIGGER!!

WHITE WIRE

TRIGGER WIRE OPTION 1 - CONNECT
TO POINTS, YELLOW WIRE ON MSD
STYLE DISTRIBUTORS OR
ACCESSORIES OR E.I. AMPLIFIER

VIOLET/GREEN WIRES

TRIGGER OPTION 2 - CONNECT TO
CRANK TRIGGER OR MSD STYLE
DISTRIBUTOR - VIOLET IS
POSITIVE - GREEN IS NEGATIVE