


SEVEN-PIN TRAILER WIRE HARNESS

INSTRUCTIONS

The trailer harness and connector must be wired as follows to trailer:



End View of Trailer Connector

- | | |
|-----------|----------------------------|
| 1. WHITE | Ground (common) |
| 2. BLUE | Electric Brakes (optional) |
| 3. GREEN | Tail & License Lamps |
| 4. BLACK | Battery (12 volts) |
| 5. RED | Left Turn and Stop Lamp |
| 6. BROWN | Right Turn and Stop Lamp |
| 7. YELLOW | Back-Up Lamps |

NOTE: Terminal 4 (battery) may be used to charge trailer battery. **CAUTION:** Battery isolator unit is not supplied with tow package. Trailer battery may discharge car battery when engine is not running. Interior trailer lamps may be powered with this circuit (up to 10 amps). Overload protection is provided by a self resetting circuit breaker or in-line fuse located in the production trailer tow harness or optional Mopar vehicle trailer tow harness available from your local dealer.