

JEGS 230-Series

Radio Specifications

FM Section

Tuner TypePLL	IF Frequency10.7MHZ
Frequency Range87.5-108 MHz	Sensitivity2.6V
Image Rejection50dB	S/N Ratio60dB
Quieting Sensitivity4uV	Capture Ratio1.5dB
T.H.D1%	Separation35dB
IF Rejection60dB		

AM Section

Frequency Range530-1710KHz	IF Frequency450KHz
S/N Ratio50dB	Sensitivity20uV
Selectivity25dB		

Audio Section

Output Channel50X4	System Power200 Watts
Output Impedance4ohm per speaker	THD0.5%
Response30Hz-18KHz		

General

Power Supply12VDC Negative Ground
Speaker impedance4-8 ohm
Stand-By Current0.02A
Chassis 200mm(7 ⁷ / ₈ ")(w)X50(2 ⁻¹ / ₄ ")mm
 X150(5 ⁷ / ₈ ")mm(D)